# Leuze

# **Technical data sheet** Light curtain receiver Part no.: 50120112 CML720i-R20-2870.R/L-M12



Leuze electronic GmbH + Co. KG 
 The Sensor People
 In der Braike 1, D-73277 Owen/Germany
 Phone: +49 7021 573-0 • Fax: +49 7021 573-199
 eng • 2025-04-04

info@leuze.com • www.leuze.com changes

## **Technical data**

Series	720
Operating principle	Throughbeam principle
Device type	Receiver
Contains	Accessories for the use of the BT-2R1
Application	Object measurement
Special version	
Special version	Crossed-beam scanning
	Diagonal-beam scanning
	Parallel-beam scanning
Optical data	
Operating range	0.3 7 m
Operating range	Guaranteed operating range
Operating range limit	0.2 9 m
Operating range limit	Typical operating range
Measurement field length	2,870 mm
Number of beams	144 Piece(s)
Beam spacing	20 mm
Measurement data	
Minimum object diameter	30 mm
Electrical data	
Protective circuit	Polarity reversal protection
	Short circuit protected
	Transient protection
Performance data	
Supply voltage U <sub>B</sub>	18 30 V, DC
Residual ripple	0 15 %, From U <sub>B</sub>
Open-circuit current	0 435 mA, The specified values refer to the entire package consisting of trans mitter and receiver.
Inputs/outputs selectable	
Output current, max.	100 mA
Input resistance	6,000 Ω
Number of inputs/outputs selectable	
Туре	Inputs/outputs selectable
Voltage type, outputs	DC
Switching voltage, outputs	Typ. U <sub>B</sub> / 0 V
Voltage type, inputs	DC
Switching voltage, inputs	high: ≥6V
	low: ≤ 4 V
Input/output 1	
Activation/disable delay	0 1 ms
-	
Time behavior	
Readiness delay	400 ms
Cycle time	4.72 ms
Response time per beam	30 µs
Interface	
Туре	IO-Link
.,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,	

	IO-Link				
	COM mode	COM2			
	Min. cycle time	COM2 = 2.3 ms			
	Specification	V1.0.1			
		V1.1			
Se	ervice interface				
Туре		IO-Link			
	IO-Link				
	Function	Configuration via software			
		Service			
C	onnection				
Νι	umber of connections	2 Piece(s)			
PI	ug outlet	Rear side			
	Connection 1				
	Connection 1 Function	Configuration interface			
		Signal IN			
		Signal OUT			
		Voltage supply			
	Type of connection	Connector			
	Thread size	M12			
	Туре	Male			
	Material	Metal			
	No. of pins	8 -pin			
	Encoding	A-coded			
	Connection 2				
	Function	Connection to transmitter			
	Type of connection	Connector			
	Thread size	M12			
	Туре	Female			
	Material	Metal			
	No. of pins	5 -pin			
	Encoding	A-coded			
M	echanical data				
Design		Cubic			
Dimension (W x H x L)		29 mm x 35.4 mm x 2,903 mm			
Ho	ousing material	Metal			
	etal housing	Aluminum			
Le	ens cover material	Plastic			
	et weight	2,950 g			
	ousing color	Silver			
Ту	pe of fastening	Groove mounting			
		Via optional mounting device			
0	peration and display				
Ту	pe of display	LED			
		OLED display			
Nι	umber of LEDs	2 Piece(s)			
Ту	pe of configuration	Software			
<b>c</b>	evetional controls	Teach-in			
U	perational controls	Membrane keyboard			
Eı	nvironmental data				
Ar	nbient temperature, operation	-30 60 °C			
Ar	nbient temperature, storage	-40 70 °C			

## **Technical data**

#### Certifications


#### Classification

Customs tariff number	90314990
ECLASS 5.1.4	27270910
ECLASS 8.0	27270910
ECLASS 9.0	27270910
ECLASS 10.0	27270910
ECLASS 11.0	27270910
ECLASS 12.0	27270910
ECLASS 13.0	27270910
ECLASS 14.0	27270910
ECLASS 15.0	27270910
ETIM 5.0	EC002549
ETIM 6.0	EC002549
ETIM 7.0	EC002549
ETIM 8.0	EC002549
ETIM 9.0	EC002549
ETIM 10.0	EC002549



### **Dimensioned drawings**

All dimensions in millimeters



- Beam spacing 20 mm А
- В Measurement field length 2870 mm
- F M6 thread G Fastening groove
- R Receiver


Т

5 mm Υ

Transmitter

### **Dimensioned drawings**





A PWR / SW IN / OUT


## **Electrical connection**

**Connection 1** 

Function	Configuration interface
	Signal IN
	Signal OUT
	Voltage supply
Type of connection	Connector
Thread size	M12
Туре	Male
Material	Metal
No. of pins	8 -pin
Encoding	A-coded

#### Pin Pin assignment

1	V+
2	IO1
3	GND
4	IO-Link
5	102
6	IO3
7	104
8	GND




#### **Connection 2**

Connection to transmitter
Connector
M12
Female
Metal
5 -pin
A-coded

#### Pin Pin assignment

1	FE/SHIELD
2	V+
3	GND
4	RS 485 Tx+
5	RS 485 Tx-



### **Operation and display**

LED	Display	Meaning
1	Green, continuous light	Operational readiness
	Green, flashing	Teach / error
2	Yellow, continuous light	Light path free, with function reserve
	Yellow, flashing	No function reserve
	Off	Object detected

#### Suitable transmitters

 Part no.	Designation	Article	Description
50119522	CML720i-T20- 2870.R-M12	Light curtain transmitter	Operating range: 0.3 7 m Connection: Connector, M12, Rear side, 5 -pin

#### Part number code

Part designation: CML7XXi-YZZ-AAAA.BCCCDDD-EEEFFF

CML	Operating principle Measuring light curtain
7XXi	Series           720i: 720i series           730i: 730i series
Y	Device type T: transmitter R: receiver
ZZ	Beam spacing 05: 5 mm 10: 10 mm 20: 20 mm 40: 40 mm
AAAA	Measurement field length [mm], dependent on beam spacing
В	Equipment A: Axial connector outlet R: Rear connector outlet
ccc	Interface L: IO-Link /CN: CANopen /PB: PROFIBUS /PN: PROFINET /CV: Analog current and voltage output /D3: RS 485 Modbus
DDD	Special equipment -PS: Power Setting
EEE	Electrical connection M12: M12 connector
FFF	-EX: Explosion protection
Note	
6 A list wi	th all available device types can be found on the Leuze website at www.leuze.com.


#### Notes

#### Observe intended use!

✤ This product is not a safety sensor and is not intended as personnel protection.

b The product may only be put into operation by competent persons.

 $\ensuremath{\mathfrak{b}}$  Only use the product in accordance with its intended use.



& For UL applications, use is only permitted in Class 2 circuits in accordance with the NEC (National Electric Code).	

These proximity switches shall be used with UL Listed Cable assemblies rated 30V, 0.5A min, in the field installation, or equivalent (categories: CYJV/ CYJV7 or PVVA/PVVA7)

#### Accessories

#### Connection technology - Connection unit

	Part no.	Designation	Article	Description
C. LEWIS	50144900	MD 798i-11-82/L5- 2222	IO-Link master	Type: IO-Link master Current consumption, max.: 11,000 mA Switching outputs for each sensor connection: 1 Piece(s) Switching output: Transistor, PNP Interface: IO-Link, Automatic protocol detection, EtherNet IP, Modbus TCP, PROFINET Connections: 12 Piece(s) Sensor connections: 8 Piece(s) Connections for voltage supply: 2 Piece(s) Interface connections: 2 Piece(s) Degree of protection: IP 67, IP 65, IP 69K

#### Connection technology - Connection cables

 Part no.	Designation	Article	Description
50135128	KD S-M12-8A-P1-050	Connection cable	Connection 1: Connector, M12, Axial, Female, A-coded, 8 -pin Connector, LED: No Connection 2: Open end Shielded: Yes Cable length: 5.000 mm Sheathing material: PUR

#### Connection technology - Interconnection cables

	Part no.	Designation	Article	Description
	50129781	KDS DN-M12-5A- M12-5A-P3-050	Interconnection cable	Suitable for interface: DeviceNet, CANopen Connection 1: Connector, M12, Axial, Female, A-coded, 5 -pin Connection 2: Connector, M12, Axial, Male, A-coded, 5 -pin Shielded: Yes Cable length: 5,000 mm Sheathing material: PUR

**Accessories** 

# Leuze

# Mounting technology - Mounting brackets

 Part no.	Designation	Article	Description
 50142900	BT 700M.5-2SET	Mounting device set	Design of mounting device: Bracket mounting Fastening, at system: Through-hole mounting, T slotted hole Mounting bracket, at device: Screw type, Sliding block Type of mounting device: Rigid Material: Steel

#### Mounting technology - Swivel mounts

	Part no.	Designation	Article	Description
ęę.	429029	BT-2RG	Mounting bracket set	Fastening, at system: Through-hole mounting Mounting bracket, at device: Clampable Type of mounting device: Turning, 360° Material: Metal, Plastic

## Configuration devices

 Part no.	Designation	Article	Description
50121098	SET MD12-US2-IL1.1 + Zub.	Diagnostics set	Interface: USB Connections: 2 Piece(s) Degree of protection: IP 20

#### Services

	Part no.	Designation	Article	Description
, U	S981001	CS10-S-110	Start-up support	Details: Performed at location of customer's choosing, duration: max. 10 hours. Conditions: Devices and connection cables are already mounted, price not including travel costs and, if applicable, accommodation expenses.
	S981005	CS10-T-110	Product training	Details: Location and content to be agreed upon, duration: max. 10 hours. Conditions: Price not including travel costs and, if applicable, accommodation expenses.

	Note
6	☆ A list with all available accessories can be found on the Leuze website in the Download tab of the article detailed page.