

# **Technical data sheet Light curtain transmitter**

Part no.: 50119517

CML720i-T20-2070.R-M12



### Contents

- Technical data
- Dimensioned drawings
- Electrical connection
- Operation and display
- Suitable receivers
- Part number code
- Notes
- Accessories





## **Technical data**



### Basic data

| Series              | 720                                   |
|---------------------|---------------------------------------|
| Operating principle | Throughbeam principle                 |
| Device type         | Transmitter                           |
| Contains            | Accessories for the use of the BT-2R1 |
| Application         | Object measurement                    |
| Special version     |                                       |

| Special version | Crossed-beam scanning  |
|-----------------|------------------------|
|                 | Diagonal-beam scanning |
|                 | Parallel-beam scanning |

### **Optical data**

| Operating range          | 0.3 7 m                    |
|--------------------------|----------------------------|
| Operating range          | Guaranteed operating range |
| Operating range limit    | 0.2 9 m                    |
| Operating range limit    | Typical operating range    |
| Measurement field length | 2,070 mm                   |
| Number of beams          | 104 Piece(s)               |
| Beam spacing             | 20 mm                      |
| Light source             | LED, Infrared              |
| Wavelength               | 940 nm                     |
|                          |                            |

#### Measurement data

| Minimum object diameter | 30 mn |
|-------------------------|-------|
|-------------------------|-------|

### **Electrical data** Protective circuit

|                               | Transient protection  |
|-------------------------------|---|
| Performance data              |   |
| Supply voltage U <sub>B</sub> | 18 30 V, DC   |
| Residual ripple               | 0 15 %, From U <sub>B</sub>   |
| Open-circuit current          | <ol> <li> 435 mA, The specified values refer<br/>to the entire package consisting of trans-<br/>mitter and receiver.</li> </ol> |

Polarity reversal protection Short circuit protected

### Time behavior

| Readiness delay | 450 ms  |
|-----------------|---------|
| Cycle time      | 3.52 ms |

### Connection

| Number of connections | 1 Piece(s) |
|-----------------------|------------|
| Plug outlet           | Rear side  |

### Connection 1

| Connection 1       |                        |
|--------------------|------------------------|
| Function           | Connection to receiver |
|                    | Sync-input             |
|                    | Voltage supply         |
| Type of connection | Connector              |
| Thread size        | M12                    |
| Туре               | Male                   |
| Material           | Metal                  |
| No. of pins        | 5 -pin                 |
| Encoding           | A-coded                |
|                    |                        |

### Mechanical data

| Design                | Cubic                        |
|-----------------------|------------------------------|
| Dimension (W x H x L) | 29 mm x 35.4 mm x 2,103 mm   |
| Housing material      | Metal                        |
| Metal housing         | Aluminum                     |
| Lens cover material   | Plastic                      |
| Net weight            | 2,200 g                      |
| Housing color         | Silver                       |
| Type of fastening     | Groove mounting              |
|                       | Via optional mounting device |

### **Operation and display**

| Type of display | LED        |
|-----------------|------------|
| Number of LEDs  | 1 Piece(s) |

### **Environmental data**

| Ambient temperature, operation | -30 60 °C |  |
|--------------------------------|-----------|--|
| Ambient temperature, storage   | -40 70 °C |  |

#### Certifications

| Degree of protection | IP 65         |
|----------------------|---------------|
| Protection class     | III           |
| Approvals            | c UL US       |
| Standards applied    | IEC 60947-5-2 |

### Classification

| Customs tariff number | 90314990 |
|-----------------------|----------|
| ECLASS 5.1.4          | 27270910 |
| ECLASS 8.0            | 27270910 |
| ECLASS 9.0            | 27270910 |
| ECLASS 10.0           | 27270910 |
| ECLASS 11.0           | 27270910 |
| ECLASS 12.0           | 27270910 |
| ECLASS 13.0           | 27270910 |
| ECLASS 14.0           | 27270910 |
| ECLASS 15.0           | 27270910 |
| ETIM 5.0              | EC002549 |
| ETIM 6.0              | EC002549 |
| ETIM 7.0              | EC002549 |
| ETIM 8.0              | EC002549 |
| ETIM 9.0              | EC002549 |
| ETIM 10.0             | EC002549 |

# **Dimensioned drawings**



All dimensions in millimeters



- Beam spacing 20 mm
- В Measurement field length 2070 mm
- M6 thread
- Fastening groove
- Profile length 2088 mm
- Transmitter
- Receiver
- 5 mm




# **Electrical connection**



### **Connection 1**

| Function           | Connection to receiver |
|--------------------|------------------------|
|                    | Sync-input             |
|                    | Voltage supply         |
| Type of connection | Connector              |
| Thread size        | M12                    |
| Туре               | Male                   |
| Material           | Metal                  |
| No. of pins        | 5 -pin                 |
| Encoding           | A-coded                |

| Pin | Pin assignment |
|-----|----------------|
| 1   | FE/SHIELD      |
| 2   | V+             |
| 3   | GND            |
| 4   | RS 485 Tx+     |
| 5   | RS 485 Tx-     |



# **Operation and display**

| LED | Display                                      | Meaning  |
|-----|--|--|
| 1   | Green, continuous light                      | Continuous mode  |
|     | Off  | No communication with the receiver / waiting for trigger |
|     | green, flashing in sync with the measurement | Measurement frequency display                            |

## Suitable receivers

| Part no. | Designation                   | Article                | Description   |
|----------|-------------------------------|------------------------|---|
| 50119971 | CML720i-R20-<br>2070.R/CN-M12 | Light curtain receiver | Operating range: 0.3 7 m<br>Interface: CANopen<br>Connection: Connector, M12, Rear side, 8 -pin                     |
| 50120190 | CML720i-R20-<br>2070.R/CV-M12 | Light curtain receiver | Operating range: 0.3 7 m Analog outputs: 2 Piece(s), Voltage, Current Connection: Connector, M12, Rear side, 8 -pin |
| 50123642 | CML720i-R20-<br>2070.R/D3-M12 | Light curtain receiver | Operating range: 0.3 7 m Interface: RS 485 Modbus Connection: Connector, M12, Rear side, 8 -pin                     |
| 50120106 | CML720i-R20-<br>2070.R/L-M12  | Light curtain receiver | Operating range: 0.3 7 m Interface: IO-Link Connection: Connector, M12, Rear side, 8 -pin                           |

### Suitable receivers



|   | Part no. | Designation                   | Article                | Description  |
|---|----------|-------------------------------|------------------------|--|
| 1 | 50123028 | CML720i-R20-<br>2070.R/PB-M12 | Light curtain receiver | Operating range: 0.3 7 m Interface: PROFIBUS DP Connection: Connector, M12, Rear side, 8 -pin    |
|   | 50131965 | CML720i-R20-<br>2070.R/PN-M12 | Light curtain receiver | Operating range: 0.3 7 m<br>Interface: PROFINET<br>Connection: Connector, M12, Rear side, 8 -pin |

### Part number code

Part designation: CML7XXi-YZZ-AAAA.BCCCDDD-EEEFFF

| CML  | Operating principle Measuring light curtain   |  |  |  |  |  |
|------|---|--|--|--|--|--|
| 7XXi | <b>Series</b> 720i: 720i series 730i: 730i series   |  |  |  |  |  |
| Υ    | Device type T: transmitter R: receiver  |  |  |  |  |  |
| ZZ   | Beam spacing 05: 5 mm 10: 10 mm 20: 20 mm 40: 40 mm   |  |  |  |  |  |
| AAAA | Measurement field length [mm], dependent on beam spacing  |  |  |  |  |  |
| В    | Equipment A: Axial connector outlet R: Rear connector outlet  |  |  |  |  |  |
| ccc  | Interface L: IO-Link /CN: CANopen /PB: PROFIBUS /PN: PROFINET /CV: Analog current and voltage output /D3: RS 485 Modbus |  |  |  |  |  |
| DDD  | Special equipment -PS: Power Setting  |  |  |  |  |  |
| EEE  | Electrical connection M12: M12 connector  |  |  |  |  |  |
| FFF  | -EX: Explosion protection   |  |  |  |  |  |
|      |   |  |  |  |  |  |

info@leuze.com • www.leuze.com

### Note



### **Notes**





### Observe intended use!



- \$ This product is not a safety sensor and is not intended as personnel protection.
- \$ The product may only be put into operation by competent persons.
- Only use the product in accordance with its intended use.

### For UL applications:



- 🔖 For UL applications, use is only permitted in Class 2 circuits in accordance with the NEC (National Electric Code).
- 🖖 These proximity switches shall be used with UL Listed Cable assemblies rated 30V, 0.5A min, in the field installation, or equivalent (categories: CYJV/ CYJV7 or PVVA/PVVA7)

### **Accessories**

# Connection technology - Interconnection cables

|  | Part no. | Designation                     | Article               | Description   |
|--|----------|---------------------------------|-----------------------|---|
|  | 50129781 | KDS DN-M12-5A-<br>M12-5A-P3-050 | Interconnection cable | Suitable for interface: DeviceNet, CANopen Connection 1: Connector, M12, Axial, Female, A-coded, 5 -pin Connection 2: Connector, M12, Axial, Male, A-coded, 5 -pin Shielded: Yes Cable length: 5,000 mm Sheathing material: PUR |

# Mounting technology - Mounting brackets

| Part no. | Designation    | Article             | Description   |
|----------|----------------|---------------------|---|
| 50142900 | BT 700M.5-2SET | Mounting device set | Design of mounting device: Bracket mounting Fastening, at system: Through-hole mounting, T slotted hole Mounting bracket, at device: Screw type, Sliding block Type of mounting device: Rigid Material: Steel |

# Mounting technology - Swivel mounts

| •   |          |             |                      |   |
|-----|----------|-------------|----------------------|---|
|     | Part no. | Designation | Article              | Description   |
| EE. | 429029   | BT-2RG      | Mounting bracket set | Fastening, at system: Through-hole mounting<br>Mounting bracket, at device: Clampable<br>Type of mounting device: Turning, 360°<br>Material: Metal, Plastic |

### **Accessories**



# Configuration devices

|     | Part no. | Designation                  | Article         | Description  |
|-----|----------|------------------------------|-----------------|--|
| is. | 50121098 | SET MD12-US2-IL1.1<br>+ Zub. | Diagnostics set | Interface: USB Connections: 2 Piece(s) Degree of protection: IP 20 |

# Services

| Part no. | Designation | Article          | Description  |
|----------|-------------|------------------|--|
| S981001  | CS10-S-110  | Start-up support | Details: Performed at location of customer's choosing, duration: max. 10 hours.  Conditions: Devices and connection cables are already mounted, price not including travel costs and, if applicable, accommodation expenses. |
| S981005  | CS10-T-110  | Product training | Details: Location and content to be agreed upon, duration: max. 10 hours. Conditions: Price not including travel costs and, if applicable, accommodation expenses.   |

### Note



🔖 A list with all available accessories can be found on the Leuze website in the Download tab of the article detailed page.